



MX-60M

TABLETOP MODEL MIXER AMPLIFIER

This compact mixer amplifier is fitted with an integrated tuner and Bluetooth-module, it can be used for numerous commercial and residential purposes. The MX-60M is fitted with an individual volume control per input channel and is protected against short circuit and thermal overload.



Pleasant background music and the right ambiance in the shop, the MX-60M makes it happen every day.



output capacity 100V	60W
output capacity RMS 8Ω	60W
frequency range	80Hz - 18kHz < 0,5% THD
zones	1
direct output	4-8Ω / 70V / 100V
tone control	yes
built-in source	USB/SD
	FM tuner
	Bluetooth
line-out	3 Pin Phoenix
MIC input	3 (1 XLR/ 2 jack 6,3 mm)
AUX input	2 RCA
priority input	1 (phoenix + contact)
priority levels	3
power supply	240V AC
dimensions (h x w x d)	76 x 270 x 230mm
weight	3,59kg

